






HP LaserJet Enterprise M750 Series Printer



Change jam recovery


This product provides a jam recovery feature that reprints jammed pages.

1. Press the Home button .



2. Press the down arrow ▼ to highlight the **Administration** menu, and then press the **OK** button.
3. Press the down arrow ▼ to highlight the **General Settings** menu, and then press the **OK** button.
4. Press the down arrow ▼ to highlight the **Jam Recovery** menu, and then press the **OK** button.
5. Press the down arrow ▼ or up arrow ▲ to highlight the appropriate setting, and then press the **OK** button. The following options are available:
 - **Auto** — The product attempts to reprint jammed pages when sufficient memory is available. This is the default setting.
 - **Off** — The product does not attempt to reprint jammed pages. Because no memory is used to store the most recent pages, performance is optimal.

CAUTION: When using this option, if the product runs out of paper and the job is being printed on both sides, some pages can be lost.

 - **On** — The product always reprints jammed pages. Additional memory is allocated to store the last few pages printed. This might cause overall performance to suffer.
6. Press the Home button  to return to the **Ready** state.